

# RE716P1TLP ( R )

## Manual Pull Station

### Product Overview

RE-716P Manual Pull Station is a high quality non-toxic die-cast manual pull station. Low profile design and smooth edges offer an attractive yet functional design. All components are pre-painted or have plated surfaces to inhibit corrosion. Electrically the RE-716P Manual pull station is unbeatable with 10 Amp snap action switch offered in all possible contact arrangements (including gold contacts). The RE-716P pull station can be used with or without a break glass rod, with replacement requiring no special tools.

### Features

- Lift and pull
- Break glass cover
- Weather and Explosion proof versions
- All stations offer hex screw or key lock access.

### Construction Material

- Painted Die Cast Housing.
- 14 Ga plated steel black plate.
- Corrosion Inhibited surfaces.
- Terminal block (4 Position)
- Single Gang Mounting
- 10 A , 120VAC snap Action Switch (S.P.S.T.)

### Specification

#### Electrical

Switch : 10A@120VAC

#### Dimensions

Station Width : 3.200 in  
Length : 4.750 in  
Depth : 0.875 in

Weight 15.5 oz / 420 grams  
Mount Single gang



### Ordering Information

MODELS	DESCRIPTION	COLOR
RE716P1T	Manual Pull station Single Action	RED
RE716P1TLP( R )	Manual Pull station Dual Action	RED



#### India:

#### RAVEL ELECTRONICS PVT LTD.,

(An ISO 9001 Company)  
150A, Electronics Industrial Estate, Perungudi, Chennai - 96 .India.  
E-Mail: marketing@ravelfire.com; Web : www.ravelfire.com

#### United Kingdom:

#### RAVEL ELECTRONICS LTD.,

Unit 11, Chancel Industrial Estate, Newhall street,  
Willenhall WV13 1NX, West Midlands, United Kingdom.  
E-mail: info@ravelfire.co.uk ;Web: www.ravelfire.co.uk