

Loop Sounder

Addressable System Single Loop System



Product Overview

- Loop powered Sounder
- Addressing by 8 way DIP switches.
- Low Standby Current.
- Slim and Sleek
- Wall or Ceiling mountable
- Loop Powered Sounder with BackBox



Features Specification:

- Loop powered Sounder
- Addressing by 8 way DIP switches.
- Low Standby Current.
- Slim and Sleek
- Wall or Ceiling mountable
- Loop Powered Sounder with BackBox

Mechanical Specification:

Models	Description
Diameter	100 mm dia
Weight	150g with base
IP Rating	IP – 42

Ordering Information

Model	Description
RE-24LS	Addressable Loop Powered Sounder

Electrical Specification:

Operating Voltage	17 ~ 28 VDC
Operating Current	15mA Max
Sound Level	85dB@1m
Sounder Type	Piezo Electric Type
Tone Type	Fire Engine Siren
Material	ABS Plastic
Mounting Type	Surface / Flush Mount
Dimensions	96 H mm X 76 L mm X 28 D mm
Back Box	95 H mm X 75 L mm X 58 D mm
Mounting Type	Surface / Flush Mount
Standby Current	0.5 mA
Loop Impedance	40 Ohms

